

ARCAM A29 Integrisano Pojačalo

Šifra: 10548
Kategorija proizvoda: Integrisana Pojačala
Proizvođač: ARCAM

Cena: 119.880,00 rsd

ARCAM A29 Integrisano Pojačalo

With

a class G amplifier, toroidal based power supply, acoustically damped chassis, complementary transistor output stages and exceptionally low levels of distortion and noise the A29 is capable of reproducing music with all its original authority and detail. Rest assured you will be hearing the music just as the artist intended. The A29 have been designed to leapfrog the competition with a massive 80 watts per channel

into 8 ohms and 175 watts into 4 ohms, allowing for huge extra power reserves from our latest generation class G topology that is both clever and efficient. During normal operation, distortion is measured in less than one part per million so that this massive power is deliver with total control and finesse. There have been great strides made in improving audio sources and loudspeakers in recent years and the time is right to match them in the field of amplifier design. This ground breaking amplifier is a must audition amplifiers for music lovers who understand that power is nothing without control.

Spec:

| | |
|---|----------------------|
| Continuous power output (20Hz—20kHz at 0.5% THD), per channel | |
| Both channels, 8Ω, 20Hz—20kHz | 80W |
| Single channel, 4Ω, at 1kHz | 175W |
| Harmonic distortion, 80% power, 8Ω at 1kHz | 0.003% |
| Inputs | |
| Phono (MM) cartridge: | |
| Input sensitivity at 1kHz | 5mV |
| Input impedance | 47kΩ + 100pF |
| Frequency response (ref. RIAA curve) | 20Hz - 20kHz ± 1dB |
| Signal/Noise ratio (AwtD) 50W, ref. 5mV input | 80dB |
| Overload margin, ref. 5mV at 1kHz | 23dB |
| Inputs: | |
| Nominal sensitivity | 1V |
| Input impedance | 10kΩ |
| Maximum input | 4.6Vrms |
| Frequency response | 20Hz - 20kHz ± 0.2dB |
| Signal/noise ratio (AwtD) 50W, ref. 1V input | 105dB |
| Preamplifier output | |
| Nominal output level | 735mV |
| Output impedance | 230Ω |
| Headphone output | |
| Maximum output level into 600Ω | 5V |
| Output impedance | 1Ω |

| | |
|---------------------------------------|-----------------------|
| Load range | 16Ω - 2kΩ |
| Accessory power output | |
| 2.1mm DC connector | 6V, 500mA |
| General | |
| Mains voltage | 110-120V or 220-240V |
| Power consumption (maximum) | 500W |
| Dimensions W x D x H (including feet) | 433 x 275 x 85mm |
| Weight (net) | 9.2kg |
| Weight (packed) | 10.7kg |
| Supplied accessories | Mains lead |
| | CR902 remote control |
| | 2 x AAA batteries |
| | Accessory power cable |