

## Pioneer XPRS102 - Aktivni zvučnik

Šifra: 17081

Kategorija proizvoda: Aktivne Zvučne Kutije

Proizvođač: Pioneer DJ

Cena: **95.880,00** rsd

The Pioneer XPRS102 features a 2000W Class-D amplifier that drives the 10" woofer and a 1" compression driver, which combine for a frequency response of 50 Hz to 20 kHz with a max SPL of 129 dB. The rear panel features a 3-input mixer with channel 1 offering a combo XLR-1/4" connector and gain control for microphone and line levels, while channel two offers a combo XLR-1/4" Hi-Z and line inputs with level gain control. Channel 3 boasts a 3.5mm line input. An XLR line output sums all channels together for adding additional speakers for better coverage. Other features include four EQ DSP modes including Live, Music, Speech, and Monitor.

### Powerful Class-D Amplification

The XPRS2 Series employs Class-D amplification with high output wattage for a powerful and premiere audio experience for performers and listeners alike. The XPRS102 full-range speaker features Class-D 2000W amplification.

### High-Quality and Robust Build

Pioneer DJ's all-new XPRS2 Series features a sleek all-black, protective plywood cabinet for performance in harsh indoor and outdoor environments. The series models all come with a durable handle to support system portability and handling during setup and take down. The XPRS2 Series also features rubber feet to create separation and shock absorption between surfaces.

### Four DSP Modes

Both of the XPRS2 full-range speakers contain four different DSP preset modes: Live, Music, Speech, and Floor Monitor to address the needs of different listening environments.

### XPRS102 Full-Range Speaker Design

The XPRS102 pairs a 10" woofer and 2.5" voice coil with a 1" exit compression driver and 1.75" voice coil to deliver pristine audio performance. Complete with a maximum sound pressure level (SPL) of 129 dB and frequency response of 50 Hz to 20 kHz, the XPRS102 full-range speakers help ensure music and spoken word reproduction is accurate and performs as intended.

### Pioneer DJ XPRS102 Specs

Configuration Active 2-Way

Enclosure Type Bass-Reflex Loudspeaker

Total Power Capacity 2000 W Peak

1000 W Program

500 W RMS

Amplifier Class Class-D

Drivers

HF Driver 1 x 1" / 25.4 mm Titanium Compression Driver

HF Voice Coil 1.75" / 4.45 cm

LF Driver 1 x 10" / 25.4 cm Woofer

LF Voice Coil 2.5" / 6.3 cm

## Performance

Frequency Response 50 Hz to 20 kHz -10 dB

Maximum SPL 129 dB (Peak)

Protections Overload, Signal Limiter, Thermal

## Connectivity

Audio I/O 1 x Combo XLR-1/4" 3-Pin Female Balanced/Unbalanced Mic/Line Input

1 x Combo XLR-1/4" 3-Pin Female Balanced/Unbalanced Line/Hi-Z Input

1 x 1/8" / 3.5 mm TRS Female Unbalanced Line Input

1 x XLR 3-Pin Balanced Mix Output

Network I/O None

USB None

Wireless Connectivity None

Signal Processing

EQ None

Parametric EQ None

Semi-Parametric EQ None

Filters None

Dynamic Processing Compression, Limiter

Phase Adjustment None

Digital Signal Processing Voicing Modes

## Power

AC Input Power 110 to 240 VAC, 50 / 60 Hz (T 10 A L 250 V)

AC Power I/O 1 x IEC Input

Power Consumption 800 W

## Physical

Mounting 1 x 1.4" / 35 mm Pole Socket (Bottom)

10 x M10 Fly Point

Handles 1 x Each Side

Construction Material Plywood

Dimensions 20.5 x 12.2 x 11.8" / 520.7 x 309.9 x 299.7 mm

Weight 34.2 lb / 15.5 kg