

MARTIN WISMAN TPU 3120 - 100V pojačalo

Šifra: 8131

Kategorija proizvoda: 100V Pojačala

Proizvođač: Martin Wisman



Cena: 32.280,00 rsd

Martin Wisman TPU 3120 - PA Amplifier, 120W

Features

- Fan-cooled
- 3 Mic and 3 Aux inputs
- 1 Line-output
- 70 V, 100 V PA-outputs
- 4-16 Ohms output for connecting a passive speaker-system for monitor
- 1 Mic-connection on the front panel, Chime button
- Build in Mp3 player with songs name display
- Treble and bass control
- 7-fold level indicator
- Master-control
- 19"-dimensions
- Protection-circuits: over current, short circuit, turn-on delay
- Screw terminals of 6 zone outputs

Specifications

MODEL	TPU-3060	TPU-3120	TPU-3180 Z6	TPU-3240 Z6
Power supply	AC110V~ 60 Hz	AC110V~ 60 Hz	AC110V~ 60 Hz	AC110V~ 60 Hz
Output power	60W RMS	120W RMS	180 W RMS	250 W RMS
Output type	70 V, 100 V or 4-16	70 V, 100 V or 4-16	70 V, 100 V or 4-16	70 V, 100 V or 4-16
Output current at 70V	0.9A	1.4A	2.5 A	3.6 A
Output current at 100V	0.6A	1.0A	1.8 A	2.5 A
Mic input	5 mV, 600 Ohms	5 mV, 600 Ohms	5 mV, 600 Ohms	5 mV, 600 Ohms
Line input	300 mV, 10 kOhms	300 mV, 10 kOhms	300 mV, 10 kOhms	300 mV, 10 kOhms

