

ZOOM ARQ - Ritam Mašina**ZOOM ARQ - Ritam Mašina**Šifra: 12024
Kategorija proizvoda: Ritam Mašine
Proizvođač: ZOOMCena: **29.880,00** rsd**CONTROLLER: PADS**

Number of pads:	96
Velocity sensitive:	Yes
Pressure sensitive:	Yes
Sensitivity curves:	4 types
Velocity (send):	Yes
Aftertouch (send):	Yes
Number of LEDs :	160
LED color:	Multi

Accelerometer:	Yes
Number of parameter knobs:	3
Number of control keys:	Base Station: 18 Ring Controller: 11

INTERFACE

USB MIDI:	Yes
Bluetooth LE:	Connect to Mac/iOS via MIDI over Bluetooth LE

LINE INPUTS

Type:	1/4" Phone
Number of inputs:	2
Function:	Line
Impedance:	50 kΩ
Gain:	+10~-65 dB
Dynamic range:	92 dB typ (IHF-A)

LINE OUTPUTS

Type:	1/4" TRS Phone
Number of outputs:	2
Impedance:	200 Ω
Dynamic range:	106 dB typ (IHF-A)

PHONES

Type:	1/4" Stereo Phone [20mW x2 [32 Ω]
Impedance:	10 Ω
Dynamic range:	102 dB typ (IHF-A)

SOUND SYSTEM

Internal sound engine:	Yes
Sampling frequency:	44.1 kHz
Bit rate:	24-bit
Maximum polyphony:	16

CONTROLLER: PADS**INTERFACE****LINE INPUTS****LINE OUTPUTS****PHONES****SOUND SYSTEM****SEQUENCER****LOOPER: AUDIO CAPTURE****MEDIA****POWER SOURCE: CONTROLLER****POWER SOURCE: BASE STATION****OS SUPPORT: BLUETOOTH LE****OS SUPPORT: USB MIDI****PHYSICAL MEASUREMENTS: BASE STATION****PHYSICAL MEASUREMENTS: CONTROLLER**

Number of instruments:	33
Number of oscillator types:	538 (468 PCM sounds + 70 synth sounds)
Number of patterns:	384 (176 preset)
Number of filter types:	7
Number of Insert FX types:	11
Number of Delay types:	3
Number of Reverb types:	3
Number of Master FX types:	14
Number of Modulation types:	8
Number of Modulations:	2
Number of Envelope Generators:	2

SEQUENCER

Number of Steps:	32
Motion Sequences:	256 motions
Song mode:	Yes
Tempo:	40.0–250.0 bpm

LOOPER: AUDIO CAPTURE

Sampling frequency:	44.1 kHz
Bit rate:	16-bit

MEDIA

Media type:	SD, SDHC, SDXC
Internal memory:	32 MB

POWER SOURCE: CONTROLLER

Type:	Li-ion Polymer, DC 4.2V maximum voltage, DC 3.7V nominal voltage, 450mAh capacity
Battery life:	About 4.5 hours (differs according to use conditions)
Recharging times:	2.5 hours

POWER SOURCE: BASE STATION

External Power:	AC adapter (AD-14)
Rated Output:	DC5V / 1A (center positive)
Power Consumption:	Max: 1.25W (No charging) Max : 4.5W (Charging)

OS SUPPORT: BLUETOOTH LE

Windows:	No
Mac OS:	10.10.4 or later
iOS:	8.0 or later

OS SUPPORT: USB MIDI

Windows:	Windows 7 SP1 or later Windows 8 (including 8.1) Windows 10
-----------------	---

CONTROLLER: PADS**INTERFACE****LINE INPUTS****LINE OUTPUTS****PHONES****SOUND SYSTEM****SEQUENCER****LOOPER: AUDIO CAPTURE****MEDIA****POWER SOURCE: CONTROLLER****POWER SOURCE: BASE STATION****OS SUPPORT: BLUETOOTH LE****OS SUPPORT: USB MIDI****PHYSICAL MEASUREMENTS: BASE STATION****PHYSICAL MEASUREMENTS: CONTROLLER****SEQUENCER****LOOPER: AUDIO CAPTURE****MEDIA****POWER SOURCE: CONTROLLER****POWER SOURCE: BASE STATION****OS SUPPORT: BLUETOOTH LE****OS SUPPORT: USB MIDI****PHYSICAL MEASUREMENTS: BASE STATION****PHYSICAL MEASUREMENTS: CONTROLLER**

Mac OS:	10.8 or later
----------------	---------------

PHYSICAL MEASUREMENTS: BASE STATION

Dimensions:	260 mm (W) x 64 mm (H) x 260 mm (D)
--------------------	-------------------------------------

Weight:	990g
----------------	------

Display:	2.0 inch (320 x 240) full color TFT
-----------------	-------------------------------------

PHYSICAL MEASUREMENTS: CONTROLLER

Dimensions:	280.5mm (W) x 33.5mm (H) x 280.5mm (D)
--------------------	--

Weight:	540 g
----------------	-------