

ART PRO AUDIO MX822CE

ART PRO AUDIO MX822CE

Šifra: 10271  
 Kategorija proizvoda: Pa Rack Ostalo  
 Proizvođač: ART

Cena: **38.400,00** rsd

Eight stereo/mono input channels with individual level, pan and effects send controls

External effects loop with independent send and return controls  
 output monitoring

Switchable low noise +48V phantom power for microphone input

Six level left and right main output metering including clip indicators

Multiple units may be chained together for additional inputs

Front  
 ampli  
 Switch  
 on Ch  
 Separ  
 for ea  
 Balan  
 Rugg

8-Channel Stereo Mixer with Effects Loop

Input Connections	XLR-F balanced (MIC) 1/4" TRS unbalanced (Ch1-Ch8, Effects Return) 1/4" TRS stereo unbalanced (EFX Buss, Main Expand)
Output Connections	XLR-M balanced (Main) 1/4" TRS unbalanced (Effectss Send) 1/4" TRS stereo unbalanced (Monitor, Main Expand, Headphone)
Input Impedance	1k Ohms (MIC), 5k Ohms (Ch1-Ch8)
Output Impedance	
Total Harmonic Distortion	<0.01% @ 1kHz
Signal to Noise Ratio	> 90dB typical (Ref 0dBu)
Maximum Input Level	-19dBu (MIC), +24dBu (Ch1-8)
Maximum Output Level	+24dBu (Main), +18dBu (Monitor, Effects Send)
Maximum Gain	+60dB (MIC), +14dB (Ch1-8)
Phantom Power	Switch Selectable, +48V DC, filtered, current limited
Power Requirements	USA - 95 to 125 VAC, 50-60 Hz Export units configured for country of destination
Dimensions	1.75"H x 19"W x 6"D (44.5mm x 483mm x 152mm)

Weight	6.5 lbs (2.95 kg)
--------	-------------------