

Saramonic VmicLink5 RX+TX+TX

Šifra: 14256
 Kategorija proizvoda: Wireless Mikrofoni
 Proizvođač: Saramonic

Cena: 85.080,00 rsd



The 5.8G

Record audio up to 30 meters away with no obstacle.

Automatic channel switch programme to avoid interference from multiple systems in the same environment.

With three discrete channel groups.

One receiver can work with up to three transmitters simultaneously.

Line & Mic inputs provide wide range of input options.

Real-time headphone monitor jack.

Detachable and flexible antenna can be rotated 360° accordingly for best sound.

Rechargeable li-ion battery (included).

RF power:	15dBm(30mW)
-----------	-------------

RF frequency:	5725-5875MHz
---------------	--------------

Channels:	3CH, RX channel changeable, TX follow with RX
-----------	---

Transmission distance:	30m with no obstacle
------------------------	----------------------

Interface:	<p>Transmitter Mic in: Max 160mV/-13dBu, 1.8V phantom power</p> <p>Transmitter Line in: Max 2V/8dBu, 50V DC isolation</p> <p>Receiver Phone out: Max 70mW/32Ω, 10V DC isolation</p> <p>Receiver Line out: 4 times mic in gain, 50V DC isolation</p>
------------	---

Receive sensitivity:	98dB
----------------------	------

THD+N:	-92dB
Sample rate:	48K/16bit
Audio frequency response:	40Hz-18KHz/±1dB
Voice delay:	18ms
Power consumption:	RX: 180mA/6V TX: 140mA/6V
Antenna gain:	3dBi
Weight:	810g
Battery:	7.2V/1000mAh Li-ion
Battery type:	LP-E17(CANON EOS M3/750D/760D)
Dimensions:	RX: 113x64x28mm; TX: 113x64x28mm
Operating temperature:	0°C-50°C
Storage temperature:	-20°C-55°C