

Adastra MM3260 - Razglasno pojačalo

## Adastra MM3260 - Razglasno pojačalo

Šifra: 15868

Kategorija proizvoda: Razglasna Pojačala

Proizvođač: Adastra

Cena: **31.080,00** rsd

### Rackmount 1U Mixer-Amp with USB/FM/BT - 2 x 60W

Rack-mountable 1U mixer-amp with built-in media player and Bluetooth receiver. 3 mono inputs connect via XLR microphone or line input (switchable). Each of these inputs has switchable +20V phantom power for use with condenser microphones or D.I. boxes and channel 1 has a variable priority function. Two stereo auxiliary line inputs are provided on RCA connectors with a stereo record output. Media player operating modes include 3.5mm Aux input, USB audio player, FM radio tuner and Bluetooth receiver for playback from a smart phone or tablet. Main left and right speaker outputs are connected via Euroblock style screw terminals and the line signal is fed to L+R XLR outputs. Perfect for local area background music and announcements or connected onto further amplifiers for larger installations.

2 x 60Wrms into 4 Ohms

Built-in Bluetooth receiver

Media player with USB playback and FM tuner

Switchable +20V phantom power

Variable priority muting for channel 1

24V emergency mute contacts

Power supply 100-240Vac, 50/60Hz (IEC)

Fuse T2AL

Output power : 4 Ohms 2 x 60Wrms

Inputs : mic/line 3 x XLR (bal/unbal)

Inputs : aux 2 x L+R RCA

Input : line 3.5mm jack to media player

Audio source Bluetooth receiver, USB & FM player

Line output L+R XLR, Record out (RCA)

Speaker outputs L+R screw terminal (Euroblock)

Emergency control 24V contacts mute all except

channel 1

Phantom power+20V (switchable channels 1-3)

ControlsMedia, 3 x Mic/Line, 2 x Aux, Treble, Bass,  
Master level

Rear panel controlsPriority muting level, mic/line and  
phantom DIP switches

Input impedance2.2k Ohms (mic/line), 10k Ohms (aux)

Frequency response : mic20Hz - 18kHz

Frequency response : line14Hz - 20kHz

Frequency response : aux10Hz - 23kHz

Input sensitivity : mic/line-45dBV

Input sensitivity : aux/line-10dBV

Signal to noise ratio : mic55dB

Signal to noise ratio : aux/line60dB

Dimensions482 x 130 x 44mm

Weight1.96kg