

Marantz CINEMA 30 Black AV risiver

Šifra: 18620

Kategorija proizvoda: AV Pojačala i Risiveri

Proizvođač: Marantz

Cena: **539.880,00** rsd



Power Amplifier

Number of Powered Channels 11

Power Output (8 ohm, 20 Hz - 20 kHz, 0.08% 2ch Drive) -

Power Output (8 ohm, 20 Hz - 20 kHz, 0.05% 2ch Drive) 140 W

Power Output (6 ohm, 1 kHz, 0.7% 2ch Drive) 175 W

Power Output (6 ohm, 1 kHz, 10% 1ch Drive) 250 W

70% Guarantee Yes

Discrete Power Amplifier Yes

Amplifier Topology Class A/B

Current Feedback Topology yes

Bi-Amp Drive assignable

Multichannel Surround Technologies

DTS DTS HD Master, DTS:X, DTS:X Pro, DTS Neural:X, DTS Virtual:X

Dolby Dolby TrueHD, Dolby Atmos, Dolby Atmos Height Virtualization, Dolby Atmos Music, Dolby Surround

Other

Max Number of Processing (Preamp) Channels 13.4

IMAX Enhanced Yes

Auro 3D Yes

Audyssey DSX Yes

Multichannel Stereo Yes

Inputs Outputs

Composite In / Out 2 / 0

Component In / Out 1 / 0

HDMI In / Out 7 / 3

Multi-Room Video Out via HDMI 0 / 0

Analog In / Fixed Level Out 3 in / 0 out

Phono (MM) In Yes

Digital In: Optical / Coaxial 2 / 2

Multi-Room Out: analog / digital 2 / 0

Multichannel Preamp Out 7.2

Subwoofer Out 4 (independent)

7.1 multichannel input No

Number of Speaker Terminals 13

Speaker A / B assignable

Multi-Room Speaker Terminal assignable

Front Inputs USB-A
USB Audio Yes / No / No
FM Tuner with RDS Yes
DAB+ Tuner No
Multi-Room Video Out: Video / HDMI 7/3
analog In/out 6 / 0
Multichannel Pre Out Yes (13.4)
Front Inputs: Audio / Composite / Digital (Opt) / HDMI / USB No / No / No / No / Yes

HDMI

Total HDMI Inputs / No. Support 8K 6 / 3
HDCP2.3 support Yes
HDMI Outputs: Main / Zone 2 / 1
Analog to HDMI Video Conversion No
HDMI Upscaling 1080P/4K to 8K
Max resolution @ framerate
Audio Return Channel ARC, eARC
Video Dynamic Range HDR / HLG / Dolby Vision / HDR10+ / Dynamic HDR
ALLM (Auto Low Latency Mode) Pass-through for gaming Yes
Variable Refresh Rate / Quick Frame Transport Yes / Yes / No
HDMI Pass-Through in Standby Mode Yes
CEC Yes
DSD Audio over HDMI No
Auto LipSync Yes
HDMI Inputs: Back / Front 7 / -
Video Conversion Analog -> HDMI Yes
HDMI to HDMI Scaling 1080P/4K to 8K
HDMI 2.1: 8K/60Hz AB / 4K/120Hz AB Yes / Yes
8K/60Hz AB / 4K/120Hz AB Pass-through In/Out 7 / 2 (up to 40Gbps)
HDMI 2.0: 3D / 4K / CEC / ARC Yes / Yes / Yes / Yes
HDR / HLG / Dolby Vision / HDR10+ / Dynamic HDR Yes / Yes / Yes / Yes / Yes
Variable Refresh Rate / Quick Flame Transport / Quick Media Switching Yes / Yes / No
8K signal pass-through / scaling / GUI overlay o / o / o
4K Signal Pass-Through / Scaling / GUI Overlay o / o / o
DSD Audio Capability Yes

Performance Technologies

Copper Plated Chassis Yes
Toroidal Power Supply Transformer Yes
Hyper Dynamic Amplifier Modules (HDAM) (List version) Yes
Pure Direct Mode Yes
Gold Plated RCA Terminals Yes
Clock Jitter Reducer Yes

Acoustic Room Correction

Audyssey MultEQ XT32
Audyssey Dynamic EQ / Dynamic Volume Yes / Yes
Audyssey LFC Yes
Dirac Live Support Yes
Variable Cross Over Yes
Optimized Bass Redirection Yes
Bass Sync Yes
Dirac Live Upgradability Yes

Music File Support

Lossy Formats MP3 / WMA / AAC
Lossless formats FLAC HD 192/24 / WAV 192/24 / ALAC 192/31
DSD Audio 2.8 MHz / 5.6 MHz
Gapless Playback FLAC, WAV, ALAC, DSD

Compressed Audio Enhancer: MDAX2 Yes
Network Audio Sharing Yes

Streaming Services

HEOS Multi-room and Streaming Yes
AirPlay Audio Streaming AirPlay2
Internet Radio TuneIn
Spotify* Spotify Connect
Pandora Yes
SiriusXM Yes
Other Streaming Services * Amazon Music HD/
Amazon Music / TIDAL / Deezer / Napster / Soundcloud / Mood Mix
Room tested Yes

Network Connectivity

Ethernet Ports Yes
Wi-Fi (include version / band) Yes
Bluetooth (Include version) Yes
Bluetooth Re-transmit for Bluetooth headphones Yes

Smart Home Integration and Control

Voice Assistant Compatibility Alexa / Google Voice Assistant / Apple HomePod
App for Smart Phones & Tablets (iOS & Android) Marantz AVR App
HEOS Multi-Room Integrated Yes
HEOS Link Compatibility: IR/ IP Yes /Yes
Multi-Room zones 2
Zone Audio Source: HDMI / Opt, Coax / Network, USB / Analog 2 Ch / 2 Ch / Yes / Yes
Zone Audio Output: Speaker / Preout Yes / Yes
Zone HDMI Output from HDMI Source Yes
Control Connectivity IP Control / RS232 Control / Web Control / App Control
IR Flasher In Yes
Marantz Remote Bus Yes
DC Trigger Output 3
HDMI Diagnostics Yes

Others

Front Display 2 line FLD + port hole OLED
Primary Display Size (diagonal in/mm)
Secondary Display Size (diagonal in/mm)
GUI Languages 3
Setup Assistant Yes
Smart Select on Remote Yes
Firmware Update by Network / USB Yes / Yes
ECO Mode Yes
Auto Power off Yes
Sleep Timer Yes
GUI Overlay on HDMI
CEC Yes
Auto Speaker Setup by Microphone Audyssey MultEQ XT32Dirac Live (upgrade)
Graphic User Interface - GUI Modern HD GUI
Smart Select Yes

General

Available Colors Black/Silver-Gold
Metal Front Panel Yes
System Remote Control RC-051SR
Power Consumption in W 780
Power Consumption No-Sound (ECO on/off) in W 65 W / 110 W

Standby Consumption in W 0.2

CEC Standby Consumption in W 0.5

Network Standby Consumption in W Less than 2.0

Maximum Dimensions

Antenna:Horizontal:(W x D x H) in mm

Antenna:Vertical :(W x D x H) in mm

W/o Antenna:(W x D x H) in mm 442 x 384 x 109

(442 x 384 x 178)

□ 442 x 372 x 109 □

Weight in kg 8.7

What's in the box Main unit, remote control, batteries, AM/FM antennas, wire labels, quick start guide, Audyssey microphone, cardboard microphone stand, 2 External Detachable Antennas, AC cord

Weight in lbs. 42.8

Maximum Dimensions

Antenna:Horizontal:(W x D x H) in inches

Antenna:Vertical :(W x D x H) in inches

W/o Antenna:(W x D x H) in inches 17.4 x 18.0 x 7.5

(17.4 x 18.0 x 10.2)

□17.4 x 17.6 x 7.5□

Pre-Programmed / Learnable / LCD Display Yes / Yes / Yes