

JBSYSTEMS LED Manager

Šifra: 2195

Kategorija proizvoda: DMX Kontrole i Dimeri

Proizvođač: JBSYSTEMS

Cena: **23.880,00** rsd

Extremely versatile power supply for all kinds of passive RGB LED-projectors.

Different standalone working modes:

Hold mode: Instant access to 9 pre-programmed colors

Static chase mode: 12 different color chases with manual speed control

Sound chase mode: 12 different color chases with audio triggering

Spectrum mix: 32 different spectrum mix colors, including nice color fades

Slow color fades with adjustable fade time

All functions can be controlled directly on the on the LED-Manager or by the optional LEDCON-01 remote.

300Watt power: 2x 150W 24Vdc outputs. (R+G+B) with short-circuit protections

3 independent programmable on/off timers. (start/stop 3 different color chases at 3 different times!)

4 DMX channels needed: Ch1=red, Ch2=green, Ch3=Blue, Ch4=Dimmer/strobe.

Fan cooling for extra reliability.

:: Technical Information

Power Input: AC 230V~ 50Hz

Fuse: 6,3A slow blow (20mm glass)

Backup batteries: 3x 1,2V AA-type NiMH rechargeable batteries (optional)

Output voltage to LEDs: DC 24V common anode

Output power to LEDs: 2x 150W max. (Total = 300W max.)

Red: 2x 50W max. (Total = 100W max.)

Green: 2x 50W max. (Total = 100W max.)

DMX connections: 3pin XLR (DMX-512 standard)

DMX channels: 4 (CH1: red, CH2: green, CH3:blue, CH4:dimmer/strobe)

Audio input: None, internal microphone

Size: 330 x 202 x 106cm (see drawing below)

Weight: 6,6kg