

MARTIN WISMAN MXR 1000

MARTIN WISMAN MXR 1000

Šifra: 7084

Kategorija proizvoda: PA Predpojačala

Proizvođač: Martin Wisman

Cena: **31.080,00** rsd

2 Channel Mixer

Features

- * 2 channel mixer of 10 inputs
- * Remote paging console GMZ 200 as mic 1 with highest input priority
- * Mic 2-4 with VOX selector over inputs 5-10 and phantom power
- * All the 10 inputs with mic, line and high pass filtering selector
- * Inputs 7-10 either by XLR mic inputs or by dual RCA line inputs
- * Dual channel XLR line outputs
- * All inputs include inputs 1-10, MIC (remote paging console GMZ 200), chime could be selected to have channel 1, channel 2 and channel 1+2 outputs.
- * Built-in 2/4 tone pre-set chime, remote chime trigger and local trigger on front panel
- * Volume controls are provided over chime, MIC1, inputs 2-10, channel 1 and channel 2 masters. Bass and treble tone control are provided for both channel 1 and channel 2.
- * Indicators for input 1-10, power and 2 channel level meters
- * AC 110 or 230V and DC 24V operation

Specifications

| | |
|-----------------------------|---|
| Model | MXR 1000 |
| Input Sensitivity/Impedance | |
| MIC/ Line | $\pm 2.45\text{mV}/5\text{K}$ balanced, $\pm 245\text{mV}/5\text{K}$ balanced |
| Line RCA In | $500\text{mV}/5\text{K}$ unbalanced |
| Output Level/Impedance | |
| Master 1, 2 | +4dBu/200 balanced |
| REC | 0dBu/10K unbalanced |
| Frequency Response | |
| Less Than | -1dB(20Hz~20KHz) |
| S/N Ratio | |
| MIC | More than 60dB |
| Line | More than 75dB |
| THD | |
| MIC | Less than 0.05% |
| Line | More than 0.03% |
| Cross-talk | |
| MIC | More than 60dB |
| Line | More than 75dB |
| Power Consumption Power | 13W |
| Power Supply | ~110V/60Hz or ~230V/50Hz & DC 24V |
| Dimensions | 484x295x44mm |
| Weight | 3.9Kg |

Pogledajte još:

[**Martin Wisman GMZ 200**](#)