

MARTIN WISMAN MXR 500

MARTIN WISMAN MXR 500

Šifra: 7083

Kategorija proizvoda: PA Predpojačala

Proizvođač: Martin Wisman

Cena: **26.280,00** rsd

Mixer Pre-amplifier

The MXR 500 is a public address pre-amplifier with five balanced MIC inputs, three AUX level inputs and one EMC(priority) level inputs.

Priority muting is achieved via MIC 2 and EMC for overriding music for paging and emergency alarms.

Individual gain controls are provided for MIC and AUX inputs, bass and treble controls are provided for overall tone control.

Features

- * 5-channel MIC input and 3-channel Aux input.
- * With 1-channel EMC input.
- * Independent volume control, MASTER volume control.
- * With compulsive insert and Priority function.
- * MIC balance input interface with phantom power.
- * Individual Gain controls for MIC
- * EMC has priority over all inputs except MIC 2
- * Bass and Treble Tone Controls
- * AC 110V or 230V and DC 24V operation

Model	MXR 500
Input Sensitivity & Impedance	MIC 2, 3, 4, 5: $\pm 2.5\text{mV}/2\text{K}$, Balanced XLR type MIC 2, 3, 4: $5\text{mV}/600$, Unbalanced TRS type AUX 1, 2, 3: $300\text{mV}/10\text{K}$, Unbalanced RCA type EMC: $775\text{mV}/47\text{K}$, Unbalanced TRS type MIC 1: $\pm 385\text{mV}/20\text{K}$, Balanced MIC I
Output Sensitivity & Impedance	MIX OUT: $\pm 775\text{mV}/470$, Balanced XLR type REC OUT: $200\text{mV}/470$, Unbalanced RCA type
Frequency Response	20Hz-20KHz($\pm 0.5\text{dB}$)
S/N Ratio	MIC input: 66dB AUX input: 80dB
THD	Less than 0.1% at 1KHz, 1/3 rated power
Tone	Bass: $\pm 10\text{dB}$ at 100Hz Treble: $\pm 10\text{dB}$ at 10KHz
Mute	MIC 1 overrides other input signals with 0-30dB attenuation
Phantom Power Protection	+48V
Power Supply	AC fuse
Dimensions	$\sim 110\text{V}/60\text{Hz}$ or $\sim 230\text{V}/50\text{Hz}$ & DC 24V
Weight	484x295x44mm 5Kg

Pogledajte još:

[Martin Wisman GMZ 200](#)