

RELOOP PLAY

RELOOP PLAY
Image or file not found or type unknown

Šifra: 7710
Kategorija proizvoda: DVS Scratch Sistemi
Proizvođač: Reloop

Cena: **4.680,00** rsd

Play

USB-DJ-audio interface with 24-Bit sound quality

Most compact format

Exter

**USB
SOUN**

With
one o
the m
Speci
club s
grant

Elaborate connecting possibilities

Thanks to the elaborate connecting possibilities, Reeloc Play offers two play modes. On the one hand there is the external mixer mode: with it, it is possible routing two separate stereo channels to an external mixer - this mode will be appreciated by all professional Traktor users. The second mode is called the controller mode: In this case a master output is routed to the sound system and it is possible to connect headphones directly to the interface - this mode is especially appropriate for laptop DJs without further hardware. Both stereo channels' volume can be comfortably adjusted via separate controllers. The signal status LEDs allow a visual monitoring so that everything remains in view and under control. Small, professional and always present: Plug&Play.

Technical Data

Minimum system requirements PC:

Windows XP (SP3), Win7
(32 bit/64 bit)

at least Pentium III /
Intel Core Duo, 1 GHz
(NO AMD processors
at least 512 MB RAM
recommended!)

Minimum system requirements Mac:

OS X 10.5/10.6

Intel Core Duo family
(only Intel MACs)
at least 512 MB RAM

Dimensions: 80 x 20 x
65 mm

Weight: 85 g

Incl. ASIO driver CD, USB
cord

Features

Ultra portable 4-channel
DJ audio interface with
24 bit resolution
Hi-speed USB 2.0 with
low latency ASIO/CORE
Audio drivers
Hi-gain outputs for
powerful club sound
2 stereo RCA outputs for
use with an external DJ
mixer
Stereo 1/4" headphones
output for use with
software mixer
2 play modes: External
mixer mode (2 separate
channels can be routed
to an external mixer),
controller mode (1x
master out is routed to
the sound system and
headphones can be
connected directly to
the interface)
Volume controls and
signal status LEDs for
direct, visual monitoring
Separate volume
controllers for channels
1 & 2, master &
headphones respectively
USB bus powered
Burglar-proof:
Kensington lock
Low latency ASIO/Core
Audio drivers
Compatible with Mac OS
X and Windows
XP/Vista/7